



ELEGANT

FURNITURE & LIGHTING™

Installation manual for:

2800D36

Dimensions:D36" H36" L24+1

Collection: Maria Theresa

Bulb Type:E12 bulb not included

Lamp Frame Weight(lbs):42

Total Weight(lbs):95



Thank you for choosing our product(s).

Our Company is actively involved in every step of the production.

Our product(s) are designed to be utilized for every application that graces your home or business.

We pride ourselves in providing the most prompt and courtesy service to all of the valued customers.

Please find the enclosed detailed instruction and read carefully for proper installation.

If you have any questions, please contact the retailer where the purchased was made.



SAFETY


Warning: MAKE SURE THE ELECTRICITY TO THE WIRES YOU ARE WORKING ON IS SHUT OFF. BY EITHER REMOVING THE FUSE OR TURNING OFF THE CIRCUIT BREAKER.

CAUTION

- Before assembling the lighting fixture, please read all instructions carefully.
- All frame & crystal components are fragile, please handle with care.
- Required supply circuit : 110 - 130V/60Hz
- Labeled wires are "L" for live wire, "N" for neutral wire, "E" for ground wire.
- Never install fixture on damp ceiling, the room should be dry and well ventilated
- All electrical components must be installed by a licensed electrician and in accordance with the National Electrical Code and the appropriate local electrical codes.

Unpack the Package

Please open the box carefully and check all the items are inside the box. If you have any installation, assembling and missing parts questions, where you purchase from and any other relevant information ready, our customer service team will provide comprehensive and worry free service to our valued customers.

Frame Parts List











2800D36 D36" H36" L24+1

Step 1

Please use the parts list to ensure you are not missing any parts













2800D36

PARTS LIST

part	picture	Description	Parts Number	Qty	Check list
ZA		4"Crossbar	CP10R53L3	1	
ZB		ø6"Canopy		1	
ZC		Canopy ring		1	
ZD		L59"Chain06T Twist Design	Chain06T	1	
ZE		Power Cord 12' SPT-2-16# Clear/Gold/Black		1	
P1		loop		1	
P2		top tier lamp body		1	
P3		top tier glass cover 6"	GD1006A60CL GD1006A60GT	2	
P4		washer		2	
P5		finial		2	


03

2800D36 D36" H36" L24+1

part	picture	Description	Parts Number	Qty	Check list
P6		bottom tier lamp body		1	
P7		4"Metal tube		24	
P8		glass dish 4.5"	GD1003G45CL GD1003G45GT	24	
P9		Lamp arm 25.7"	ARM10280026A	8	
A		1050-14#*2+911-2.5"		8	
B		1050-14#*1+911-2.5"		8	
C		1050-14#*1+911-2.0"		120	
D		1050-14#*4+911-3.0"		16	
E		1050-14#*4+911-3.0"		16	
F		1050-14#*7+911-3.0"		8	
G		1050-14#*7+911-3.0"		8	
H		1050-14#*7+911-3.0"		8	

04

Step 2 Canopy Installation Instruction




"L" = Hot wire
 "N" = Neutral wire
 "E" = Ground wire






IMPORTANT: Test sockets with bulb before dressing the fixture.

- 1 .Drill a $\phi 0.7$ " hole in the ceiling reinforcement to allow a $\frac{11}{16}$ " threaded rod to pass through.
- 2 .Attach the electrical box to the ceiling reinforcement and pass the $\frac{11}{16}$ " threaded rod through the box and secure it to the heavy duty hickey.
- 3 .Pass the fixture wires and ground wire through the loop, canopy ring, center hole of canopy and the heavy duty hickey.
- 4 .Pull ceiling wires down through the fixture box and make connection.
- 5 .Screw loop only onto threaded pipe.
- 6 .Hang the fixture on chain.
- 7 .Secure the canopy with canopy ring.

Frame Assembly Diagram



lamp body(04)parts list

- A1-lamp body 
- A2-cover 
- A3-glass dish 
- A4-washer 
- A5-finial 

Step 3

Frame Assembly Instructions






Installation:

Please read all instructions carefully.
 Before you proceed to install, make sure that the power supply is turned off and remains off until installation is complete.
 Please note that each part has been assigned a number.
 Please proceed in a numerical order.

1. Fix the crossbar(01) to the junction box.
2. Hang the chain(03) on the loop.
3. Break up the lamp body(04) (08), assemble the lamp arm(05) to the lamp body and connect all wires correctly.
4. Assemble the lamp body which broke up just now.
5. Connect the main wire at the junction box correctly.
6. Fix the canopy cover to the ceiling.
7. Hang the glass dish(07) and Metal tube(06) on the lamp arm.
8. As the crystal dressing instruction, hang the crystal parts.

The end!

lamp body(08)parts list

- B1-lamp body 
- B2-cover 
- B3-glass dish 
- B4-washer 
- B5-finial 

Step 4 Crystal Dressing Instructions


1. Hang crystal "A", "B", "C", "D", "E", "F", "G", "H", "N", "P", "Q", "R".

2. Connect both ends of O with A,
 Connect both ends of M with B,
 Connect both ends of L with D,
 Connect both ends of K with E,
 Connect both ends of J with F,
 Connect both ends of I with G.

Crystal Dressing Diagram



When dressing the chandelier with the crystals please remember to wear either rubber or cotton gloves. So as to prevent any damage or smudging on the crystals.



Congratulations !

You are now done installing your Elegant Lighting fixture. Sit back and admire each crystal as it will become the statement piece for your room/house.

Thank you.

Cleaning and Maintenance of Chandelier Frame

The finish on our chandelier frames and fixture frames is protected by a durable coating of lacquer. To clean, use a clean soft, dry cloth. Do not use any metal polishes, cleaners, abrasives or any substance which could remove the protective finish. Failure to follow these instructions automatically voids the guarantee.

Cleaning and Maintenance of Crystals

Wet a soft cotton fabric in clean warm water and wipe gently, then polish with a dry soft cotton fabric.

To Order Crystal Replacement Parts

Should you require replacement crystals or pins (the metal connectors attaching the crystals), contact the store where the product was purchased. For ease of ordering, you may use the original crystal trimming instructions provided with this product and circle the items you wish to order, indicating the quantity by writing the number needed adjacent to the circle. You will be contacted with prices prior to shipment. All orders must be pre-paid.

Elegant Lighting Warranty

The finish and frame of your new chandelier or fixture are warranted for a period of one (1) year from the date of purchase. Our company will, at its option, repair or replace any frame that has a defect in the materials or workmanship during the warranty period. All crystals are guaranteed for their original quality during the life of the chandelier. Breakage is not covered by this warranty.

To make a claim under this warranty, contact our customer service department.

A written return authorization form will be sent to you with specific instructions.

Returns and Conditions of Warranty

Returns must be pre-authorized by contacting the retailer where you made your purchase..Returns will only be accepted with a written return merchandise authorization and return shipping charges pre-paid. We reserve the right to inspect all returned merchandise to fully determine the nature of any defect. This guarantee shall not apply to any product that has been changed, altered or otherwise modified, nor shall it apply to any product that has been repaired or altered by anyone other than a pre-authorized facility. We will not be responsible for any breakage or damages incurred during transit, nor for crystal parts or metal frame part that have been subject to misuse, negligence, accident or inappropriate handling. Also, we will not be held responsible for damage incurred during improper installation or wiring by others, nor for damages resulting from a failure to follow the recommended maintenance or installation procedures. This guarantee is issued in lieu of any and all other guaranteed or warranty, whether written or implied and any and all other obligations or liabilities. Further, we neither authorize nor permit any other person or firm to assume for us, any liability in connection with the sale of our products.